

DeWALT INVERTER PETROL GENERATOR 2000W

DXGNi20E



Features

- Economy Mode automatically adjusts engine speeds to save fuel and reduce sound emissions
- Integrated Off/Run/Choke Knob simplifies startup procedures
- Covered outlets provide added protection from the environment
- The engine speed adjusts automatically and precisely to the corresponding load
- The practical overload protection ensures that the unit switches off automatically if the load is too high
- Our low oil shutdown to the automatic prevents damage the engine



PERFORMANCE			
Power Supply	230V ~ 50/60 Hz	Amperage	7.8 A
Starting Watts	2000 W	Rated Watts	1800 W
ENGINE			
Engine	80i	Engine Type	4-stroke OHV single Cylinde
Noise Level	64 dB (a) (7 m)	Displacement	79.9 cc
OVERALL DESIGN			
Fuel Tank	5 L	Fuel Consumption	≤395 (g/kW-h)
Oil Capacity	0.35 L	Sarting Mode	Recoil Starter
GENERATOR SET			
Length	498 mm	Width	335 mm
Height	459 mm	Net Weight	22 KG