

Features

- Economy Mode automatically adjusts engine speeds to save fuel and reduce sound emissions
- Integrated Off/Run/Choke Knob simplifies startup procedures
- Covered outlets provide added protection from the environment
- The engine speed adjusts automatically and precisely to the corresponding load
- The practical overload protection ensures that the unit switches off automatically if the load is too high
- Our low oil shutdown to the automatic prevents damage the engine



PERFORMANCE			
Power Supply	230V - 50/60 Hz	Amperage	13.9 A
Starting Watts	3500 W	Rated Watts	3200 W
ENGINE			
Engine	160 VI	Engine Type	4-stroke OHV single cylinder
Noise Level	58 dB (a) (7 m)	Displacement	163 cc
OVERALL DESIGN			
Fuel Tank	8 L	Fuel Consumption	≤395 (g/kW-h)
Oil Capacity	0.45 L	Starting Mode	Electric
GENERATOR SET			
Length	580 mm	Width	345 mm
Height	520 mm	Net Weight	28.5 KG