

DeWALT INVERTER PETROL GENERATOR 4200W

DXGNi42E



Features

- Economy Mode automatically adjusts engine speeds to save fuel and reduce sound emissions
- Integrated Off/Run/Choke Knob simplifies startup procedures
- Covered outlets provide added protection from the environment
- The engine speed adjusts automatically and precisely to the corresponding load
- The practical overload protection ensures that the unit switches off automatically if the load is too high
- Our low oil shutdown to the automatic prevents damage the engine



PERFORMANCE			
Power Supply	230V ~ 50/60 Hz	Amperage	16.5 A
Starting Watts	4200 W	Rated Watts	3800 W
ENGINE			
Engine	175 ViE	Engine Type	4-stroke OHV single cylinder
Noise Level	63 dB (a) (7 m)	Displacement	174 cc
OVERALL DESIGN			
Fuel Tank	8 L	Fuel Consumption	≤395 (g/kW-h)
Oil Capacity	0.45 L	Sarting Mode	Electric
GENERATOR SET			
Length	580 mm	Width	380 mm
Height	540 mm	Net Weight	30 KG